

FO patch panel OV-A

19"/1U, loaded

splice box with adapters and pigtails



Fibre optic splice box OV-A, 19"/1U, extractable, configuration example with 24 SCD adapters and 48 pigtails

PRODUCT INFORMATION

APPLICATION	For the termination of fibre optic cables - maximum of 48 fibres. Loaded with FO adapters, ready for splicing prepared pigtails (2 m, colour code: IEC 60304), splice trays, splice holders and splice protection in crimp technology.	
DESCRIPTION	Housing:	metallic, extractable drawer with locking mechanism, can be upgraded to OV-AT using telescopic slides: allows for depth-adjustable mounting of box (5 steps, maximum 50 mm)
	Colour:	similar to RAL 7035
	Imprint:	numbers (silk screen printing) on frontplate
	Capacity:	up to 48 fibres
	Strain relief:	with cable tie and screwed cable gland (M20)
	Cable entry:	rear left and right
	Dimensions:	19"/1U, depth 254 mm
CONNECTOR SYSTEM	Adapter:	SCD, LCD, LSH, ST
SCOPE OF DELIVERY	Included are: - coloured pigtails with measurement report - FO adapters, fastened by screws - splice trays with cover - splice protection in crimp technology - splice holder - fastening set	
NOTE	Variants on request	

FO patch panel OV-A

19"/1U, loaded

splice box with adapters and pigtails

PRODUCT INFORMATION

Article No.	Description	Loaded with	
190968	Splice box, OV-A, extractable, 1U	6x LCD adapter, blue polymer housing	with ceramic sleeve and 12 LC pigtails 2 m E09/125µm OS2
190969	Splice box, OV-A, extractable, 1U	6x LCD adapter, beige polymer housing	with ceramic sleeve and 12 LC pigtails 2 m G50/125µm OM2
190884	Splice box, OV-A, extractable, 1U	6x LCD adapter, turquoise polymer housing	with ceramic sleeve and 12 LC pigtails 2 m G50/125µm OM3
190975	Splice box, OV-A, extractable, 1U	12x LCD adapter, blue polymer housing	with ceramic sleeve and 24 LC pigtails 2 m E09/125µm OS2
190988	Splice box, OV-A, extractable, 1U	12x LCD adapter, beige polymer housing	with ceramic sleeve and 24 LC pigtails 2 m G50/125µm OM2
190885	Splice box, OV-A, extractable, 1U	12x LCD adapter, turquoise polymer housing	with ceramic sleeve and 24 LC pigtails 2 m G50/125µm OM3
191761	Splice box, OV-A, extractable, 1U	24x LCD adapter, blue polymer housing	with ceramic sleeve and 48 LC pigtails 2 m E09/125µm OS2
191762	Splice box, OV-A, extractable, 1U	24x LCD adapter, beige polymer housing	with ceramic sleeve and 48 LC pigtails 2 m G50/125µm OM2
191763	Splice box, OV-A, extractable, 1U	24x LCD adapter, turquoise polymer housing	with ceramic sleeve and 48 LC pigtails 2 m G50/125µm OM3
190989	Splice box, OV-A, extractable, 1U	6x LSH/APC adapter, green polymer housing	with ceramic sleeve and 6 LSH/APC pigtails 2 m E09/125µm OS2
190990	Splice box, OV-A, extractable, 1U	6x LSH adapter, black polymer housing	with ceramic sleeve and 6 LSH pigtails 2 m G50/125µm OM3
190893	Splice box, OV-A, extractable, 1U	12x LSH/APC adapter, green polymer housing	with ceramic sleeve and 12 LSH/APC pigtails 2 m E09/125µm OS2
190886	Splice box, OV-A, extractable, 1U	12x LSH adapter, black polymer housing	with ceramic sleeve and 12 LSH pigtails 2 m G50/125µm OM3
190894	Splice box, OV-A, extractable, 1U	24x LSH/APC adapter, green polymer housing	with ceramic sleeve and 24 LSH/APC pigtails 2 m E09/125µm OS2
190887	Splice box, OV-A, extractable, 1U	24x LSH adapter, black polymer housing	with ceramic sleeve and 24 LSH pigtails 2 m G50/125µm OM3
190888	Splice box, OV-A, extractable, 1U	6x SCD adapter, blue polymer housing	with ceramic sleeve and 12 SC pigtails 2 m E09/125µm OS2
190974	Splice box, OV-A, extractable, 1U	6x SCD adapter, beige polymer housing	with PB sleeve and 12 SC pigtails 2 m G50/125µm OM2
190882	Splice box, OV-A, extractable, 1U	6x SCD adapter, turquoise polymer housing	with PB sleeve and 12 SC pigtails 2 m G50/125µm OM3
190889	Splice box, OV-A, extractable, 1U	12x SCD adapter, blue polymer housing	with ceramic sleeve and 24 SC pigtails 2 m E09/125µm OS2
190955	Splice box, OV-A, extractable, 1U	12x SCD adapter, beige polymer housing	with PB sleeve and 24 SC pigtails 2 m G50/125µm OM2
190883	Splice box, OV-A, extractable, 1U	12x SCD adapter, turquoise polymer housing	with PB sleeve and 24 SC pigtails 2 m G50/125µm OM3
190973	Splice box, OV-A, extractable, 1U	24x SCD adapter, blue polymer housing	with ceramic sleeve and 48 SC pigtails 2 m E09/125µm OS2
190972	Splice box, OV-A, extractable, 1U	24x SCD adapter, beige polymer housing	with PB sleeve and 48 SC pigtails 2 m G50/125µm OM2
190991	Splice box, OV-A, extractable, 1U	24x SCD adapter, turquoise polymer housing	with PB sleeve and 48 SC pigtails 2 m G50/125µm OM3
190971	Splice box, OV-A, extractable, 1U	6x ST adapter, metal housing	with ceramic sleeve and 6 ST pigtails 2 m E09/125µm OS2
191757	Splice box, OV-A, extractable, 1U	6x ST adapter, metal housing	with PB sleeve and 6 ST pigtails 2 m G50/125µm OM2
191758	Splice box, OV-A, extractable, 1U	6x ST adapter, metal housing	with PB sleeve and 6 ST pigtails 2 m G50/125µm OM3
191759	Splice box, OV-A, extractable, 1U	12x ST adapter, metal housing	with ceramic sleeve and 12 ST pigtails 2 m E09/125µm OS2
191760	Splice box, OV-A, extractable, 1U	12x ST adapter, metal housing	with PB sleeve and 12 ST pigtails 2 m G50/125µm OM2
190880	Splice box, OV-A, extractable, 1U	12x ST adapter, metal housing	with PB sleeve and 12 ST pigtails 2 m G50/125µm OM3
190999	Splice box, OV-A, extractable, 1U	24x ST adapter, metal housing	with ceramic sleeve and 24 ST pigtails 2 m E09/125µm OS2
191764	Splice box, OV-A, extractable, 1U	24x ST adapter, metal housing	with PB sleeve and 24 ST pigtails 2 m G50/125µm OM2
190881	Splice box, OV-A, extractable, 1U	24x ST adapter, metal housing	with PB sleeve and 24 ST pigtails 2 m G50/125µm OM3

All pigtails are coloured (in accordance with IEC 60304), stripped and stored in splice tray

Copper

Fibre Optics

Cabinets & Racks

Data Centre

Wireless

Multimedia

General Information